

# 12 V Car power inverter, 500 W

FG-PWC-033

## **PURE POWER**

- A 230V power source in your car
- Practical USB port for charging mobile devices





#### **Features**

- Single socket 500 W car power inverter
- Allows to connect any AC powered electronics (max. 500 Watt), like notebooks, HiFi or video equipment, chargers of mobile phones/cameras, electrical tools etc.
- Overloadand short-circuit protection, plus a built-in cooling fan provide a stable power supply

10

CN

0.037908

260x155x75 mm

8716309075930 8504408490

540x390x180 mm

15.77

- LED status indicators and alarm buzzer
- Replaceable fuses

#### Packaging

Q'ty in crtn, pcs Crtn volume, CUM Crtn weight, kgs Individual package size LxWxH: Carton size LxWxH: Country of origin Barcode Customs code

#### Package contents

Car power inverter Cigarette lighter cable Crocodile clamp power cables User manual

Specifications

Input: 11-15 VDC (car cigarette lighter or accumulator directly)

Output: 230 VAC +/10% at 50 Hz (+/-3Hz), modified sine wave

Power output: 500 W continuous power (peak power 1000 W) USB power output: 5 V / 1 A

Recommended operating temperature: +5...+35 °C (max -15...+50 ° C)

Material: aluminium and plastic Cable: 600 mm (power x 5 sq.mm), 0.55 m (cigarette lighter cable, 1.5 sq.mm) Dimensions: 230 x 100 x 60 mm

System requirements

Safety precautions:

A car cigarette lighter normally provides power up to 240 W. If your electrical equipment consumes more than 150 W make sure the cigarette lighter does not get hot, otherwise reconnect the inverter to car's accumulator directly, being careful with the polarity.

### Certificates



Copyright © 2009–2017, Gembird Software Ltd.

Wittevrouwen 56 | 1358CD Almere | The Netherlands | Phone: +31-36-5211588

www.energenie.com | postmaster@energenie.com